

WM30 Wind Sensor for Mobile Applications



The WM30 provides accurate wind measurement in a compact and economical package.

Features/Benefits

- Combined wind speed and direction sensor with affordable price
- Compact and light design is optimal for mobile applications
- Low power consumption
- Fast and linear response to wind
- Choice of one-wiper or two-wiper potentiometer models

The Vaisala Wind Sensor WM30 is a compact and economical wind speed and direction sensor. The rotating cup anemometer at the top of the unit provides a linear response to wind speed. The vane, which is attached to the body of the unit, provides a fast response to wind direction.

Accurate wind measurement

The shape, dimensions, and material of the cups contribute to accurate measurement. The cups are carefully tested to give linear response between the wind speed and the angular velocity of the cup wheel.

The wind vane is located directly beneath the cup assembly and is made of a durable, lightweight material that ensures fast response and low inertia.

Flexible outputs

A relay contact output is provided for wind speed. The wind speed can be recorded either by counting the number of pulses within a fixed time period, or by measuring the time between successive pulses.

A potentiometer detects the position of the vane. The potentiometer features low starting and running torque, linear resistance and a long operation life. It has a single wiper with an open gap of less than 5 degrees. With constant voltage supplied to the potentiometer, the output voltage is directly proportional to the azimuth angle.

Optimal for low-power applications

The electronics are designed specifically for applications where low power consumption is essential.

Built for harsh conditions

The cups and vane are made of reinforced PA plastic which guarantees a rigid structure even at the highest wind speeds.

The electronics are located inside an anodized aluminium core which creates not only a firm body, but a watertight enclosure for the electronics as well. This provides full protection against water, dust, pollutants and electromagnetic interference.

Easy installation

A mast adapter for a 30 mm tube is supplied with the sensor. An installation kit for larger tube diameters, 50 ... 110 mm, is available as an option.

Technical data

Wind speed

Measurement range	0.5 ... 60 m/s
Starting threshold	< 0.4 m/s
Distance constant	2 m
Transducer output	1 Hz ~ 0.7 m/s
Accuracy (within range 0.4 ... 60 m/s)	
wind speed < 10 m/s	± 0.3 m/s
wind speed > 10 m/s	± 2%
Characteristic transfer function	$U = -0.24 + 0.699 \times F$
	(where U = wind speed [m/s], F = output frequency [Hz])

Wind direction

Measurement range	
WMS301 with 1-wiper potentiometer	0 ... 355°
WMS302 with 2-wiper potentiometer	0 ... 360°
Starting threshold	< 1.0 m/s
Damping ratio	0.3
Overshoot ratio	0.4
Delay distance	0.6 m
Accuracy	better than ±3°

General

Supply voltage	3 ... 15 VDC
Electrical connections	5-pin male with 12 mm threads
Recommended connector at cable end	BINDER 99 1436 814 05
Operating temperature	-40 ... +55 °C (-40 ... +131 °F)
Storage temperature	-60 ... +65 °C (-76 ... +149 °F)
Material	
housing	AlMgSi, gray anodized
cups	PA, reinforced with carbon fibre, black
vane	PA, reinforced with fiberglass, white
Dimensions	265 (h) × 360 (Ø) mm
Weight	360 g

Accessories

Mounting adapter	WMS30KIT
Sensor connector	19370
Sensor connector and cable, 10 m	19904

Test compliance

Wind tunnel tests	ASTM standard method D5366-93 ASTM standard method D5096-90
-------------------	--

Complies with EMC standard EN61326-1:1997 + Am1:1998 + Am2:2001; Generic Environment

VAISALA

For more information, visit
www.vaisala.com or contact
us at sales@vaisala.com

Ref. B210384EN-B ©Vaisala 2009
This material is subject to copyright protection, with all copyrights retained by Vaisala and its individual partners. All rights reserved. Any logos and/or product names are trademarks of Vaisala or its individual partners. The reproduction, transfer, distribution or storage of information contained in this brochure in any form without the prior written consent of Vaisala is strictly prohibited. All specifications — technical included — are subject to change without notice.

